

## TECHNICAL INFORMATIONS

# CHAMA / CANDLE E14

## 4W 4000K

Lâmpadas LED decorativas com diferentes potencias, ideais para substituir as antigas lâmpadas de vela incandescentes.

Decorative LED lamps with different wattages, ideal for replacing old incandescent candle lamps.

Bombillas LED decorativas con diferentes potencias, ideales para reemplazar lámparas de vela incandescentes.




### ILAR-00311


REFERENCE		DIMENSION & WEIGHT		PHOTOMETRICAL DATA	
Reference	ILAR-00311	Diameter	37mm	Total Luminous Flux	330lm
Lamp type	C37	Length	100mm	Luminous Efficacy	82.5lm/W
Lamp Base	E14	Weight	20g	Beam Angle	180°
Nominal Lifetime (EOL end of life)	25000h			Colour Temperature	4000K
Switching Cycle (times)	15000X			Colour Rendering Index	80
Dimmable	No			Colour Consistency	<= 6
Mercury Free	Yes				

ELECTRICAL AND OPERATING DATA		ENERGY LABEL & STANDARS		CERTIFICATIONS	
Power Rated	4W	Energy Label	A+	ROHS	YES
Equivalent Wattage	30W	Energy Consumption KWH/1000H	4kWh	CE	YES
Lamp Current	42mA			LM70	NO
Nominal Voltage	220-240V			LM80	YES
Operating Frequency	50/60Hz			LM79	-
Power Factor	0.5			TM21	-
Starting Time	0.5s			ENEC	-
Warm-up Time (60%)	0.5s				
Operating Temperature	-30°C to + 40°C				

### SIZE



### BEAM ANGLE



Designed by Aron Light in Portugal. Made in PRC

